



PULSEAUDIO™

6X6 AUDIO DISTRIBUTION AMPLIFIER



- 6x6 AUDIO MATRIX WITH BRIDGEABLE ZONES TO ACCOMMODATE 1 OR 2 SPEAKERS PER ZONE
- PROVIDES A WHOLE HOUSE AUDIO CONTROL SYSTEM - EXPANDABLE UP TO 3 UNITS FOR 18 ZONES OF DISTRIBUTED AUDIO
- INTEGRATED WIFI ADAPTER AND ANDROID AND IOS APP ALLOWS FOR EFFORTLESS CONTROL VIA SMARTPHONE OR TABLET
- OPTIONAL KEYPADS WITH MODERN DESIGN FITS SEAMLESSLY INTO ANY ROOM KEYPADS ARE POE WITH BUILT-IN IR RECEIVERS (KEYPADS AND 1 CAT5E/CAT6 CONNECTION HUB INCLUDED WITH PART #PA66KIT)
- HIGH EFFICIENCY CLASS D AMPLIFICATION
- STEREO/BRIDGE MONO OUTPUT
- STEREO/BRIDGE MODE ADJUSTABLE
- IR REMOTE INCLUDED FOR SOURCE SELECT/VOLUME/TREBLE/BASS
- RS-232 PORT FOR 2 WAY COMMUNICATION WITH THE HOME AUTOMATION SYSTEMS
- POWER 230V AND 115V ADJUSTABLE
- EXT. MUTE & SYSTEM ON 3.5MM MONO MINI PHONE JACKS
- 6 IR EMITTER 3.5 MM MONO MINI PHONE JACKS + 1 IR EMITTER 3.5 MM MONO FOR ALL OUTPUT JACK
- 1 PA INPUT JACK TO SET ALL ZONE TO SOURCE 1
- 3 ZONE PRE-AMP OUTPUTS TO CONNECT EXTERNAL POWER AMPLIFY
- EFFORTLESSLY INTEGRATE AND CONTROL YOUR STREAMING SERVICES WITH CASATUNES MULTI-ROOM, MULTI-MODE MUSIC SERVERS



**PART NUMBER:
PA66AMP and PA66KIT**

Pulseaudio1.com